



ARTEX ELT 345

Emergency Locator Transmitter

406
MHz



Worldwide Coverage

The ELT 345 boasts an industry low price for an ELT providing the same quality and performance on which the ARTEX brand was built. GPS data is embedded within the first emergency transmission and provides Search and Rescue personnel with the aircraft location, within 100 meters, in less than a minute.



ARTEX ELT 345

406 MHz Emergency Locator Transmitter

How the ARTEX ELT 345 works

The ARTEX ELT 345 can be activated manually (via cockpit remote switch or ELT switch) or automatically (the G-Switch senses a 2.3G or greater impact), and alerts the closest Search and Rescue agency of your emergency. The 406 MHz signal, containing your GPS coordinates, is transmitted to the Cospas-Sarsat satellites and relayed to the Mission Control Center where it is immediately routed to the nearest Search and Rescue agency. Your beacon's registration will tell first responders **who** you are and the beacon itself lets them know **where** you are to within 100 meters. Finally, the local 121.5 MHz homing signal assists Search and Rescue forces to identify your exact location.

Ease of Installation

The ARTEX ELT 345 provides a quick-and-easy retrofit opportunity with flexible installation options such as a two-wire remote switch that does not require any aircraft

power. Because it is a single output ELT, the ELT 345 utilizes the same RF output and only one coax cable to transmit both 406 MHz and 121.5 MHz signals. The built-in navigational interface does not require aircraft power to operate which greatly reduces the cost of installation. The stainless steel mounting bracket has a multiple-hole pattern configuration which makes the replacement of legacy ARTEX ELTs or old ACK, Kannad and AmeriKing ELTs quick and easy.

Pair the ELT 345 with ARTEX's exclusive online satellite confirmation testing system, 406Test.com, and get real-time beacon testing results, from the same satellites used by Search and Rescue, to ensure your ELT system is functioning properly. There is a reason that ARTEX ELTs are the choice of more aircraft manufacturers than any other; they trust ARTEX to build the highest quality products knowing they are used to save lives.



Worldwide Coverage



Battery:
6-year Lithium LiMnO₂

SPECIFICATIONS

Operating Frequencies

121.5 MHz +/-6.075 kHz
(Emission Designator 3K20A3X)
406.040 MHz +/- 1 kHz,
(Emission Designator 16K0G1D)
Depending on Cospas-Sarsat TAC

Output Power

406 MHz: 5W for 24 hours @ -20°C to +55°C
(-4°F - 131°F) 121.5 MHz: 50 mW for 50 hours
@ -20°C to +55°C (-4°F - 131°F)

Output Connector

BNC Female

Activation

Automatic by 4.5 ft/sec (2.3 G) Primary G-Switch
and Manual Activation

Battery

6-year Lithium LiMnO₂

Temperature Certified to:

Operating: -20°C to +55°C (-4°F - 131°F)
Storage: -55°C to +85°C (-67°F - 185°F)

Self-Test Checks

G-Switch Enabled
406 MHz and 121.5 MHz Power
NAV system
Low Battery

Remote Control

On/Arm/Test

Mounting Hardware

ELT 345 Mounting Tray: 8323

Other Parts

Coax Cable and Antenna
Audio Buzzer (alerts ground crews of inadvertent activations)
Remote Switch

Weights (with tray)

Total Weight: 2.00 lbs (907.19 g)

Measurements

ELT Transmitter with mounting hardware installed:
6.40 (L) x 2.96 (H) x 3.78 (W) inches
(16.26 x 7.52 x 9.60 cm)

ELT KIT COMPONENTS

ELT KIT	BEACON & BATTERY	SWITCHES	ANTENNAS
P/N 8102	8100	8304	8324



Remote Switch
8304



Whip Antenna
8324



406 ELT
8100



Mounting Bracket
8323

Features of the ELT 345

- Automatic Fixed (AF) Emergency Locator Transmitter
- Designed for a quick and easy first-time or retrofit installation in experimental and general aviation aircraft
- Single antenna output for emergency transmission on both 406 MHz (Cospas-Sarsat) and 121.5 MHz (local Search & Rescue) frequencies
- Enhanced position accuracy within 100 meters through a built-in GPS interface (NMEA 0183 or RS 232)
- Test the ELT and installation with a satellite-based online confirmation test via ARTEX's proprietary satellite testing service 406Test.com
- New hermetically sealed G-Switch for increased reliability
- Aviation grade connectors and cabling included

- Includes the ELT 345 transmitter, dual band whip antenna, 2 wire remote switch, mounting tray and all required hardware for less than \$600
- If you use it... ARTEX will replace it, Free of charge. Learn more at Survivorclub.com
- COSPAS-SARSAT Approved. Visit www.ACRARTEX.com for all approvals
- New stainless steel mounting bracket has a multiple hole pattern configurations to replace legacy ARTEX ELTs as well as ACK, Kannad or AmeriKing ELTs
- 2 wire interface that doesn't require aircraft power
- Encoded digital message broadcasts aircraft identification/registration providing access to owner/emergency contact details
- Worldwide coverage

Why Choose Artex?

Boeing
Cessna
Hawker Beechcraft
Piper
Cirrus
Diamond
Quest
Gulfstream
Bombardier/Learjet
Embraer
Sikorsky
Bell
U.S. Military
Because They Do

For further information please contact:

ARTEX Products

ACR Electronics, Inc.
5757 Ravenswood Road
Fort Lauderdale, FL 33312

Tel: (954) 981.3333
Fax: (954) 983.5087
Email: sales@acrartex.com