

#### **RADIANT Pocket Radio V1.0**

last revised July 16, 2018

Radiant Pocket Radio V1.0 is our first aircraft band receiver. It is awesome for checking ATIS before getting in your plane. It's also loaded with features.

#### **SIX** reception bands

- Aircraft band, 118.000 --- 137.975 mhz
- AM 520 1720 khz
- FM 87.5 108.0 Mhz
- Shortwave 5.95 21.65
  Mhz
- CB 25 28 Mhz
- VHF 136 174 Mhz

## Small size, 100 x 60 x 15mm (3.93 x 2.36 x 0.59")

## **Excellent sensitivity**

- Aircraft band, 2uv
- AM 3mV/M
- FM 2 uv
- Shortwave 30 dB uV
- CB 1 uV
- VHF -5dB uV

#### **FEATURES & SPECIFICATIONS**

- ✓ Small size, less than 4" tall
- ✓ Six bands
- ✓ Excellent sensitivity
- ✓ Runs on 2 AAA batteries (not included)
- ✓ Includes strap

- ✓ Clock and Alarm
- ✓ Backlight
- ✓ Channel Storage
- ✓ Micro USB connector for power
- ✓ Retractable Antenna



Radiant Pocket Radio

DISCLAIMER: Products from RADIANT Technology are not designed to be used in applications where their failure would endanger safe flight or human life in any way. They are intended solely for use in VFR conditions. They are not certified to meet any Technical Standard Order and are not produced under a Parts Manufacturing Authority (TSO / PMA). As a result, they are suitable only for use in experimental and ultralight aircraft, and in Light Sport Aircraft, if meeting the requirements of the respective manufacture.

WARRANTY: Your new RADIANT Technology instrument carries a one year warranty. Please contact us at <a href="mailto:info@beliteaircraft.com">info@beliteaircraft.com</a> should your product need warranty service. International warranty service will be charged US\$50.00 for repairs, which includes return shipping after repair. Payment must be received before service begins. RETURN/REFUND INFORMATION: Must be returned in new, resalable condition within 14 days.

CONTACT: <u>info@beliteaircraft.com</u>, 316-253-6746 / RADIANT Technology/Belite Enterprises LLC, 8610 E. 34<sup>th</sup> Street N. Wichita KS 67226



#### **RADIANT Pocket Radio V1.0**

last revised July 16, 2018

Radiant Pocket Radio V1.0 is our first aircraft band receiver. It is awesome for checking ATIS before getting in your plane. It's also loaded with features.

## **SIX** reception bands

- Aircraft band, 118.000 --- 137.975 mhz
- AM 520 1720 khz
- FM 87.5 108.0 Mhz
- Shortwave 5.95 21.65
  Mhz
- CB 25 28 Mhz
- VHF 136 174 Mhz

# Small size, 100 x 60 x 15mm (3.93 x 2.36 x 0.59")

## **Excellent sensitivity**

- Aircraft band, 2uv
- AM 3mV/M
- FM 2 uv
- Shortwave 30 dB uV
- CB 1 uV
- VHF -5dB uV

## **FEATURES & SPECIFICATIONS**

- ✓ Small size, less than 4" tall
- ✓ Six bands
- ✓ Excellent sensitivity
- ✓ Runs on 2 AAA batteries (not included)
- ✓ Includes strap

- ✓ Clock and Alarm
- ✓ Backlight
- ✓ Channel Storage
- ✓ Micro USB connector for power
- ✓ Retractable Antenna



Radiant Pocket Radio

DISCLAIMER: Products from RADIANT Technology are not designed to be used in applications where their failure would endanger safe flight or human life in any way. They are intended solely for use in VFR conditions. They are not certified to meet any Technical Standard Order and are not produced under a Parts Manufacturing Authority (TSO / PMA). As a result, they are suitable only for use in experimental and ultralight aircraft, and in Light Sport Aircraft, if meeting the requirements of the respective manufacture.

WARRANTY: Your new RADIANT Technology instrument carries a one year warranty. Please contact us at <a href="mailto:info@beliteaircraft.com">info@beliteaircraft.com</a> should your product need warranty service. International warranty service will be charged US\$50.00 for repairs, which includes return shipping after repair. Payment must be received before service begins.

RETURN/REFUND INFORMATION: Must be returned in new, resalable condition within 14 days.